

MS SERIES | INVERTER/CHARGER

PURE SINE WAVE DESIGNED FOR DEMANDING APPLICATIONS

Introduction

The MS Series inverter/charger is a line of pure sine wave inverters designed for mobile, backup, and off-grid applications. MS Series inverter/chargers are powerful, easy-to-use, and best of all, cost effective.



Features

- Pure Sine Wave – Power your sensitive electronics without worry. The MS Series provides reliable, utility-grade power.
- Power Factor Corrected (PFC) Charger – Our PFC charger is built into all of our inverter/chargers. It uses less energy from a generator than a standard charger – 25-30% less AC current than standard chargers.
- Battery Profile Presets – Using the ME-RC, ME-ARC, or ME-MR Remote Controls, easily choose from and set standard battery profiles, including Lithium Iron Phosphate (LFP) – only available via the ME-RC and ME-MR, Gel, Flooded, AGM1, and AGM2.
- Convenient Wiring Access – An extra large AC access cover with terminal screw block and 360° DC connection terminals with covers make wiring easier.
- Choices – The MS Series is available in 12, 24, and 48-volt configurations.
- Versatile Mounting – Mount the MS Series inverter/charger on a shelf, bulkhead, or even upside down.
- Multiple Ports – The MS Series provides multiple ports, including an RS485 communication port for network expansion, and a remote port.
- Convenient Switches – The MS Series comes with an on/off inverter-mounted switch with an easy-to-read LED indicator.
- Expanded Transfer Relay – 60 Amp transfer service is available on all models except MS2000, which is 30 Amp only.

Model Numbers

- MS2000
- MS2000-15B
- MS2000-20B
- MS2012
- MS2012-15B
- MS2012-20B
- MS2024
- MS2812
- MS4024 (series stackable)
- MS4048
- MS4048-20B

Available For

- Backup Systems
- Marine Systems
- Off-Grid Systems
- RV Systems
- Trucks

Available Accessories

- AGS
- Battery Monitor Kit
- Conduit Box
- DC Load Disconnect
- Remote Switch Adapter
- Fuse Blocks
- MagWeb
- Remote - ME-ARC
- Remote - ME-MR
- Remote - ME-RC
- RV-C Bridge - ME-RVC
- Smart Battery Combiner



Pure Sine Wave



12, 24, 48 Battery Voltage Options



2000-4000 W Continuous Output Options



SPECIFICATIONS

	MS2000/12 MS2012 (-15/-20B)	MS2812	MS2024	MS4024	MS4048 MS4048-20B
INVERTER SPECIFICATIONS					
Input battery voltage range	9 - 16.8 VDC	9 - 16.8 VDC	18 - 33.6 VDC	18 - 33.6 VDC	36 - 67.6 VDC
AC output voltage accuracy	120 VAC ± 5%	120 VAC ± 5%	120 VAC ± 5%	120 VAC ± 5%	120 VAC ± 5%
Output frequency and accuracy	60 Hz ± 0.1 Hz	60 Hz ± 0.1 Hz	60 Hz ± 0.1 Hz	60 Hz ± 0.1 Hz	60 Hz ± 0.1 Hz
Total Harmonic Distortion (THD)	< 5%	< 5%	< 5%	< 5%	< 5%
1 msec surge current (amps AC)	50	70	75	120	120
100 msec surge current (amps AC)	33	40	37	82	72
5 sec surge power (real watts)	3300	3900	2850	5800	8500
30 sec surge power (real watts)	3100	3800	2750	5400	5750
5 min surge power (real watts)	2800	3200	2700	4900	5250
30 min surge power (real watts)	2200	3000	2200	4500	4750
Output power (continuous watts)	2000	2800	2000	4000	4000
Maximum continuous input current	267 ADC	373 ADC	133 ADC	267 ADC	133 ADC
Inverter efficiency (peak)	90.6%	90%	86%	93.7%	94%
AC Relay Transfer time (minimum)	16 msec	16 msec	16 msec	16 msec	16 msec
Power Consumption - searching	<8 watts	<8 watts	<8 watts	<8 watts	<8 watts
Power Consumption - inverting (no load)	25 watts	30 watts	25 watts	25 watts	25 watts
Output Waveform	Pure Sine Wave	Pure Sine Wave	Pure Sine Wave	Pure Sine Wave	Pure Sine Wave
CHARGER SPECIFICATIONS					
Continuous output at 25° C	100 ADC	125 ADC	60 ADC	105 ADC	60 ADC
Charger efficiency	85%	85%	85%	85%	85%
Power factor	> .95	> .95	> .95	> .95	> .95
Input current for continuous rated output	15 AAC	18 AAC	7.9 AAC	29 AAC	30 AAC
GENERAL FEATURES AND CAPABILITIES					
Transfer relay capability	30 ACC max. each input (30AC total on MS2000 models, 60ACC total on all other models)*				
Five stage charging capability	Bulk, Absorb, Float, Equalize (requires remote), and Battery Saver™				
Battery temperature compensation	Standard with available temp sensor connected (battery temp 0-50° C)				
Internal cooling	0 to 120 cfm variable speed drive using dual 92mm brushless DC fans				
Overcurrent protection	Yes, with two overlapping circuits				
Overtemperature protection	Yes on transformer, MOSFETS, and battery				
Corrosion protection	Yes, PCB's conformal coated, powder coated chassis/top, and stainless steel fasteners				
Branch-rated output circuit breakers	Optional on the MS2000 (15 or 20 amp breakers), MS2012 (15 or 20 amp breakers) or MS4048 (20amp breakers)				

Warranty	Three years parts and labor				
PHYSICAL SPECIFICATIONS					
Dimensions (l x w x h)	13.75" x 12.65" x 8.0" (34.9 cm x 32.1 cm x 20.3 cm) [Height on MS2000: 7.0"/17.8 cm]				
Mounting	Shelf or wall (vents not allowed to face downward unless ME-CB or MMP/MP is installed)				
Unit weight	42 lb (19.1 kg)	55 lb (24.9 kg)	41 lb (18.6 kg)	55 lb (24.9 kg)	55 lb (24.9 kg)
Shipping weight	48 lb (21.8 kg)	62 lb (28.1 kg)	49 lb (22.2 kg)	62 lb (28.1 kg)	62 lb (28.1 kg)
Max operating altitude	15,000' (4570 m)	15,000' (4570 m)	15,000' (4570 m)	15,000' (4570 m)	15,000' (4570 m)
Temperature (Operating/Non-operating)	-20° C to +60° C (-4° F to 140° F) to -40° C to +70° C (-40° F to 158° F)				
Operating humidity	0 to 95% RH non-condensing				



GENERAL NOTES

*The pass-thru capability on each leg of the -15B and -20B models is limited by the output breaker size on each output. Testing for specifications at 25° C. Specifications subject to change without notice.



AGENCY APPROVALS & CERTIFICATIONS

- ETL Listed to UL/cUL 458, UL 1741, CSA C22.2 #107.1-01, meets KKK-A-1822E standard**
- The MS2000, MS2012, MS2812, MS4024 and MS4048 are ETL Listed to the stringent requirements of UL/cUL 458 for mobile use.
- The MS2012, MS2812, MS4024 and MS4048 are ETL Listed UL 1741 and CSA C22.2 #107.1-01 for renewable energy installations.
- All models also meet KKK-A-1822E standards for emergency vehicle use.**

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

651-653-7000
800-553-6418
InverterInfo@sensata.com

Power Conversion
www.magnum-dimensions.com