

RD-E SERIES | INVERTER/CHARGER

Introduction

Sensata Technologies now offers the RD-E Series Inverter/Charger for 230 VAC / 50 Hz installations. The RD-E Series comes with all of the features you've come to expect from a Magnum brand product, including: Power Factor Corrected (PFC) Charger: Our PFC charger is built into all of our inverter chargers. It uses less energy from a generator than a standard charger – using 25-30% less AC current than standard chargers. Battery temp sensor: The standard battery temp sensor monitors temperatures from 0 - 50° C. Convenient switches: All RD-E Series models come with an on/off inverter-mounted switch with an easy-to-read LED indicator.



Features

- Easy-to-install – Install the RD-E Series in four easy steps. See your installation manual for specific instructions.
- Versatile mounting – Mount the RD-E Series on a shelf or wall.
- Multiple ports – The RD-E Series provides multiple ports, including an RS485 communication port for network expansion, and a remote port.
- Accessible design – The extra large AC access cover with terminal screw block and 360° DC connection terminals with covers make this inverter easily accessible.
- Buy with ease – The RD-E Series is backed by a two-year (24-month) limited warranty.

Model Numbers

- RD2624E

Available For

- Renewable Energy Systems
- Off-grid Power
- Back-up Power

Available Accessories

- AGS
- Battery Monitor Kit
- Conduit Box
- DC Load Disconnect
- Fuse Blocks
- Ignition Switch Lockout
- Remote - ME-RC
- Remote - ME-ARC
- Remote Switch Adapter



Modified Sine Wave



24

Battery Voltage Options



2600-4000 VA

Continuous Output Options



SPECIFICATIONS

	RD2624E
INVERTER SPECIFICATIONS	
Input battery voltage range	18 - 32 VDC
Nominal AC output voltage	230 VAC \pm 5%
Output frequency and accuracy	50 Hz \pm 0.4 Hz
1 msec surge current (amps AC)	85
100 msec surge current (amps AC)	22
5 sec surge power (real watts)	4700
30 sec surge power (real watts)	4100
5 min surge power (real watts)	3350
30 min surge power (real watts)	2700
Continuous power output at 25° C	2600 VA
Maximum continuous input current	172 ADC
Inverter efficiency (peak)	91%
Transfer time	30 ms
Search mode (typical)	< 7 watts
No load (230 VAC output, typical)	22 watts
Waveform	Modified Sine Wave
CHARGER SPECIFICATIONS	
Continuous output at 25° C	75 A
Charger efficiency (peak)	87%
Power factor	> 0.95
Input current at rated output (AC amps)	11.5
GENERAL FEATURES AND CAPABILITIES	
Transfer relay capability	30 AAC
Five stage charging capability	Bulk, Absorb, Float, Equalize (requires remote), and Battery Saver™
Battery temperature compensation	Yes, 15 ft Battery Temp Sensor standard
Internal cooling	0 to 120 cfm variable speed
Overcurrent protection	Yes, with two overlapping circuits
Overtemperature protection	Yes on transformer, MOSFETS, and battery
Corrosion protection	Yes, PCB's conformal coated, powder coated chassis/top, and stainless steel fasteners
Output circuit breaker	NA
Input circuit breaker	30 AAC
Listings	None
Warranty	Two years

ENVIRONMENTAL SPECIFICATIONS	
Temperature (Operating/Non-operating)	-20° C to +60° C (-4° F to 140° F) to -40° C to +70° C (-40° F to 158° F)
Operating humidity	0 to 95% RH non-condensing
PHYSICAL SPECIFICATIONS	
Dimensions (h x w x d)	13.75" x 12.65" x 8.0" (34.9 x 32.1 x 20.3 cm)
Mounting	Shelf (top or bottom up) or wall
Weight	42 lb (19 kg)
Shipping weight	47 lb (21.3 kg)
Max operating altitude	15,000' (4570 m)



GENERAL NOTES

Testing for specifications at 25° C.
 Specifications subject to change without notice.

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

651-653-7000
 800-553-6418
InverterInfo@sensata.com

Power Conversion
www.magnum-dimensions.com