

PT-100 | CHARGE CONTROLLER

MAXIMIZE ENERGY HARVEST AND IMPROVE BATTERY LIFE

Introduction

The PT-100 is a Maximum Power Point Tracker (MPPT) charge controller designed to harvest the maximum available energy from the PV array and deliver it to the batteries. The PT-100's MPPT algorithm finds the maximum power point of the array and operates at this point while regulating the output current to 100 amps and battery voltage to fully charge the battery.



Features

- High Efficiency – The PT-100 provides typical 99% conversion efficiency and uses less than four watts of power in nighttime mode.
- MPPT – Maximum Power Point Tracking technology for increased PV power output efficiency.
- Voltage Options – Compatible with 12, 24, or 48V battery systems with automatic detection of system voltage. The PT-100 will produce up to 100 amps regardless of battery voltage.
- Supports a Large PV Array – A single controller supports a large PV array up to 6600W. Larger PV arrays may be used because the PT-100 is current limited to 100 amps for maximum harvest.
- Optimal Battery Charging – Automatic battery temperature compensation using an included external temperature sensor for optimum battery charging, even during extreme temperature changes.
- Multi-stage Charging – Maximizes system performance and improves battery life.
- GFDI: Integrated PV Ground-Fault Detection and Interruption/Indication, with pre-fault leakage/diagnostic metering.
- LED Indicators and Screen – Multiple LED indicators and large digital LED screen on front panel for easy-to-read system information.
- On-site Updates – The PT-100's software can be updated on site.
- Extensive Electronic Protection – Over-temperature protection, power derating when temperature is high, PV short circuit and high PV input shutdown, output overcurrent protection and night-time back-feed (reverse current) protection.
- AFCI – An integrated PV Arc-Fault Circuit Interrupter detects, indicates, and extinguishes series arcs.
- Convenient Installation – Run all of the wiring to the unique, remain-in-place wiring box with ease prior to installing the full PT-100 unit.
- Easy MP and MMP integration – The PT-100 is designed to work with a Magnum Panel (MP) or Mini-Magnum Panel (MMP). It provides room and access to PV and battery disconnect breakers.

Model Numbers

- PT-100

Available For

- Renewable Energy Systems
 - Off-grid Power
 - Back-up Power

Available Configurations

- Works as a stand-alone controller using internal settings
- Works with a Magnum Inverter/Charger and Magnum Remote. Menu settings for the PT-100 are currently only available via the ME-ARC Remote or ME-ARTR Router.

Works With

- ME Series
- MM-AE Series
- MM-E Series
- MMS Series
- MMS-E Series
- MS Series
- MS-AEJ Series
- MS-E Series
- MSH Series
- MS-PAE Series
- MS-PE Series
- MMP Panel System
- MMP-E Panel System
- MP Panel System
- MP-E Panel System
- RD Series
- RD-E Series

Optional Remote (Requires Magnum Inverter)

- Built-in programmable auxiliary relay for device control.
- Internal data logging functionality keeps energy harvest information and battery Ahr/W/hr data up to 255 days. Use the optional remote to display this information.



SPECIFICATIONS

PT-100	
ELECTRICAL SPECIFICATIONS	
Maximum PV input voltage (any condition)	200 VDC + battery voltage or 240 VDC - whichever is lower
Maximum PV operating voltage	187 VDC
Maximum PV array short circuit current	100 ADC
Nominal battery voltage range	12, 24, or 48 VDC
Battery charger output voltage range	10 to 66 VDC
Continuous charger output current	100 ADC (from -20° C to +40° C) with proportional power reduction up to 60° C ambient
Maximum output power	6600 watts
Efficiency	99% typical
Tare loss / nighttime power consumption	<4 watts (fan off, display/LEDs off)
Charger regulation method	Automatic three-stage (bulk, absorption, float) charge with manual equalization
GENERAL FEATURES AND CAPABILITIES	
Battery temperature compensation	With Battery Temperature Sensor (BTS) connected (battery temperature -20° C to +55° C)
Internal cooling	Using dual ball-bearing fans for long life
Overcurrent protection	With two overlapping circuits
Over-temperature protection	On transformer and MOSFETS
Listings	ETL Listed to UL/cUL 1741, CSA C22.2 #107.1-01, CE
Warranty	Five years parts and labor
ENVIRONMENTAL SPECIFICATIONS	
Operating temperature	-20° C to +60° C (-4° F to 140° F)
Nonoperating temperature	-40° C to +70° C (-40° F to 158° F)
Operating humidity	0 to 95% RH non condensing
PHYSICAL SPECIFICATIONS	
Enclosure type	Indoor, ventilated, with removable powder-coated conduit box
Unit dimensions (w x h x d)	8.5" x 15.5" x 4.0" (21.6 cm x 39.4 cm x 10.2 cm)
Shipping dimensions (w x h x d)	11.5" x 19.5" x 8.125" (29.2 cm x 49.5 cm x 20.6 cm)
Mounting	Mounted on a vertical surface (wall) or installed on MP or MMP enclosure
Weight	13.6 lb (6.2 kg)
Shipping weight	18 lb (8.2 kg)
Max operating altitude	15,000' (4570 m)



GENERAL NOTES

Testing for specifications at 25° C.
Specifications subject to change without notice.



AGENCY APPROVALS & CERTIFICATIONS

- ETL Listed to UL/cUL 1741, CSA C22.2 #107.1-01, CE

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

651-653-7000
800-553-6418
InverterInfo@sensata.com

Power Conversion
www.magnum-dimensions.com