

MS-E SERIES | INVERTER/CHARGER

PURE SINE WAVE

Introduction

Magnum Energy now offers the MS-E Series Inverter/Charger for 230 VAC/50 Hz installations. The MS-E Series comes with all of the features you've come to expect from a Magnum product, including: Power Factor Corrected (PFC) Charger: Our PFC charger is built into all of our inverter/chargers. It uses less energy from a generator than a standard charger – using 25-30% less AC current than standard chargers. Safe and reliable: The MS-E Series is listed to the stringent CE requirements, ensuring the inverter/charger is safe and reliable. Easy-to-install: Install the MS-E Series in four easy steps: simply connect the inverter's output to your distribution circuits or electrical panel, connect your utility power cable to the inverter's easy-to-reach terminal block, connect the batteries, and switch on the power.



Features

- Pure sine wave – Power your T.V.s, stereos, plasma screens, and other sensitive electronics without worry. The pure sine wave inverter and power factor corrected charger provide clean, reliable inverter power with low total harmonic distortion (THD) of less than 5%.
- Versatile mounting – Mount the MS-E Series on a shelf, wall, or even upside down.
- Lightweight – The lightweight aluminum base and cover also provides noise reduction and corrosion resistance.
- Multiple ports – The MS-E Series provides multiple ports, including an RS485 communication port for network expansion, and a remote port.
- Accessible design – The extra large AC access cover with terminal screw block and 360° DC connection terminals with covers make this inverter more accessible when it needs to be.
- Convenient switches – The MS-E Series comes with an on/off inverter-mounted switch with an easy-to-read LED indicator.
- Buy with ease – The MS-E Series is backed by a two-year (24-month) limited warranty.

Model Number

- MS2712E

Available For

- Renewable Energy Systems
 - Off-grid Power
 - Back-up Power
- Marine Systems
- Caravan Systems
- Truck Systems

Available Accessories

- AGS
- Battery Monitor Kit
- Conduit Box
- DC Load Disconnect
- Fuse Blocks
- Ignition Switch Lockout
- MMP-E
- Remote - ME-RC
- Remote - ME-ARC
- Remote Switch Adapter



Pure Sine Wave



12

Battery Voltage Options



1500-2700 VA

Continuous Output Options



SPECIFICATIONS

	MS2712E
INVERTER SPECIFICATIONS	
Input battery voltage range	9 - 17 VDC
Nominal AC output voltage	230 VAC \pm 5%
Output frequency and accuracy	50 Hz \pm 0.4 Hz
Total Harmonic Distortion (THD)	< 5%
1 msec surge current (amps AC)	45
100 msec surge current (amps AC)	21
5 sec surge power (real watts)	4100
30 sec surge power (real watts)	3750
5 min surge power (real watts)	3600
30 min surge power (real watts)	3500
Continuous power output at 25° C	2700 VA
Maximum continuous input current	360 ADC
Inverter efficiency (peak)	86%
Transfer time	~ 20 ms
Search mode (typical)	9 watts
No load (230 VAC output, typical)	34 watts
Waveform	Pure Sine Wave
CHARGER SPECIFICATIONS	
Continuous output at 25° C	125 ADC
Charger efficiency (peak)	83%
Power factor	> .95
Input current at rated output (AC amps)	8.5
GENERAL FEATURES AND CAPABILITIES	
Transfer relay capability	30 amps AC
Five stage charging capability	Bulk, Absorb, Float, Equalize (requires remote), and Battery Saver™
Battery temperature compensation	Yes, 4.6 m (15') Battery Temp Sensor standard
Internal cooling	0 to 120 cfm variable speed drive using dual 92mm brushless DC fans
Overcurrent protection	Yes, with two overlapping circuits
Overtemperature protection	Yes on transformer, MOSFETS, and battery
Conformal coating on PCB's for corrosion protection	Yes
Powder coated chassis & top for corrosion protection	Yes
Stainless steel fasteners for corrosion protection	Yes
Listings	CE
Warranty	Two years

ENVIRONMENTAL SPECIFICATIONS	
Temperature (Operating/Non-operating)	-20° C to +60° C (-4° F to 140° F) to -40° C to +70° C (-40° F to 158° F)
Operating humidity	0 to 95% RH non-condensing
PHYSICAL SPECIFICATIONS	
Dimensions (l x w x h)	34.9 cm x 32.1 cm x 20.3 cm (13.75" x 12.65" x 8.0")
Mounting	Shelf (top or bottom up) or wall
Unit weight	25.0 kg (55 lb)
Shipping weight	28.2 kg (62 lb)
Max operating altitude	4570 m (15,000')



GENERAL NOTES

Testing for specifications at 25° C.
Specifications subject to change without notice.



AGENCY APPROVALS & CERTIFICATIONS

- CE

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

651-653-7000
800-553-6418
InverterInfo@sensata.com

Power Conversion
www.magnum-dimensions.com